



# Digital Pulse Oximeter

Quick non-invasive device to measure pulse & SpO<sub>2</sub>



## FACT BOX

**Product Code:**  
**MD1913**

**Product Category:**  
Diagnostics.

**Product Approvals:**  
CE marked.

### Accuracy:

SpO<sub>2</sub> range is 70-100% with an accuracy of  $\pm 2\%$ .  
Pulse rate range 25-250 with an accuracy of  $\pm 3$ BPM (beats per min).

### Accessories:


x1 Pulse Oximeter  
x1 Lanyard  
x1 User Manual  
x2 AAA Batteries  
x1 Certificate Card

### Power:

2 x AAA Batteries.  
Auto-off function.



Low Power Consumption



Rotate Display



Real-time Readings

Medicare LifeSense® Fingertip Pulse Oximeter is to measure your SpO<sub>2</sub> levels and pulse. This means it checks how well your heart is pumping oxygen through your body. It is used to monitor any type of condition that can affect blood oxygen levels such as COPD, Asthma, Pneumonia, Lung Cancer, Anaemia and Congenital heart defects. The Medicare LifeSense® Bluetooth Pulse Oximeter Pulse oximetry is a quick, non-invasive and completely painless test which gives a quick and accurate results within 10 seconds.

## FEATURES

- OLED display.
- Pulse rate beep sound synchronised with heartbeat.
- Pulse bar graph and SpO<sub>2</sub> waveform display.
- Four directions display.

## DIRECTIONS:

Place finger in oximeter and press button. The measurement interface will appear in 3 seconds and results will show in 10 seconds.

## RECOMMENDED USE:

It is used to monitor any type of condition that can affect blood oxygen levels such as COPD, Asthma, Pneumonia, Lung Cancer, Anaemia and Congenital heart defects.



@Medicarefirstaid



@Medicarefirstaid



@Medicare1staid